



MS28

Features:

- Zinc die-cast housing, nickel-plated
- Excellent quality component, professional circuit design and low loss
- 13/18V supplied by satellite receiver through coaxial cable to switch corresponding port
- Capable of connecting two SATV signals simultaneously, which is switched through 13/18V
- Distributed into eight subscribers to use simultaneously and no mutual interference
- Applicable to multi-satellite and multi-receiver usage
- Power supplied from satellite receiver or external power

MS28 Specifications :

Item	Specification	Item	Specification
Frequency Range	950-2150(MHz)	DC Power Consumption	30(mA)
Insertion Loss	5(dB)	DC Max Power Passing	500(mA)
Isolation	25(dB)	Supply Voltage	20V (±1) 350mA
Return Loss	10(dB)	Impedance(all ports)	75(Ω)
Normal Working Voltage	12-20(V)		

- Switching Voltage : 13/18V
- Connectors:“F” type female

Leo Technology and Marketing Co.,Ltd.

56/32 Moo.1 Soi.Thai-It, RattanaTibeth Road. Tambon.Saima, Aumpur.Muean, Nonthaburi 11000
 Tel. +66-2926-1870-3, Fax. +66-2924-6644, Website. www.leotech.co.th